
Hamilton[®] making connections beautifully

Code: 7G2MBTPBL-B Hartland G2 | HARTLAND G2 RANGE | Rocker Switches


Product Image



Wiring



Dimensions



Insert Type	1 gang 10A Triple Pole Rocker
Insert Colour	Black/Black
EAN13 Barcode	5051164004620
Commodity Code	85363010
Luckins TSI	407519738
Dimensions(Nominal)	Single: Height = 87.4mm Width = 87.4mm Depth = 4.65mm
Weight	117 GR
Fixing Hole Centres	Box Fixing = 60.3mm
Switched Poles	Triple
Current Rating	10A
Voltage	220/250V AC
Maximum Load	10 Amp resistive
Mains Frequency	50Hz
IP Rating	IP2XD
Contact Gap Minimum	3mm
Terminal Capacity 1	5 x1mm²
Terminal Capacity 2	4x1.5mm²
Terminal Capacity 3	1x2.5mm²
Terminal Capacity 4	1x4mm² Multi-strand
Terminal Capacity 5	1x6mm²
Earth Terminal Capacity 1	5x1mm²
Earth Terminal Capacity 2	4x1.5mm²
Earth Terminal Capacity 3	3 x2.5mm²
Earth Terminal Capacity 4	1x4mm² Multi-strand
Earth Terminal Capacity 5	1x6mm²
Product Class 1	Must be earthed
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS EN 60669-1

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com | W: www.hamilton-litestat.com

All accessories are manufactured under an accredited BS EN ISO 9001:2015 Quality Management System. It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. This datasheet was generated on 4/17/2023 10:31:14 AM E&OE