

5 **5 Years**
Product Warranty
UK Only

2 **2 Years**
On-Site Warranty
Main-land UK Only



Mulu DALI

07645 MUL0105/DA

Mulu Emergency Bulkhead DALI 5W IP65 6500K White

- DALI-2 conforming to EN 62386-202
- Maintained and non-maintained option
- All legends included
- 20mm Conduit entry
- IP65 and IK10 (vandal resistant) for internal & external uses
- Dual entry push-wire terminal block for easy loop-in loop-out wiring
- BESA box fitting points



Overview

Mulu LED Emergency Exit Sign or Emergency Bulkhead Luminaire is a self-contained, multi-purpose, non-maintained or maintained 3-hour emergency luminaire solution. It can be used with or without the emergency exit graphics and is supplied with adaptable self-adhesive graphics for escape routes guidance.



General Information

IK Rating	IK10
IP Rating	IP65
Protection Rating	Class II
Installation Area	Internal and External

Technical Summary

Product Code	MUL0105/DA
Lumens Output Maximum	160 lm
Dimensions (L x W x D) (mm)	352x110x67
UEM/EME Battery Life	4 y
UEM/EME Input Voltage	220-240Vac 50/60Hz
UEM/EME Ambient Temperature Range	0°C to 40°C
UEM/EME CCT	6,500 K
UEM/EME Input Power (Max)	5 W
UEM/EME Weight	0.5 kg

Compliance

Others UKCA, CE, RoHS, WEEE, REACH

Tel: 01635 523 713

Email: sales@kosnic.com

Kosnic.com



Kosnic Lighting KosnicUK KosnicLightingUK

5 **5 Years**
Product Warranty
UK Only

2 **2 Years**
On-Site Warranty
Main-land UK Only

Overview

Mulu LED Emergency Exit Sign or Emergency Bulkhead Luminaire is a self-contained, multi-purpose, non-maintained or maintained 3-hour emergency luminaire solution. It can be used with or without the emergency exit graphics and is supplied with adaptable self-adhesive graphics for escape routes guidance.



General Information

IK Rating	IK10
IP Rating	IP65
Protection Rating	Class II
Installation Area	Internal and External

Mulu DALI

07645 MUL0105/DA

Accessories

Product Code	Description	Type
BAT18LFP2/L	Battery for Emergency sign DALI of MULU NITRO DOXA ORDA 3W	Battery
BATS18LFP1	Battery for DD EME 2, Doxa 2 & EME light 2 in 1, Temp sensor	



Tel: 01635 523 713

Email: sales@kosnic.com

Kosnic.com



Kosnic Lighting KosnicUK KosnicLightingUK KosnicUK